

SP (Pixel Multiplying Technology) EVENT PRODUCTS – January 2009

This product's list cancels and replaces any previous release. In order to improve products and technology continuously and meet the requirements of an ever evolving marketplace, the manufacturer reserves the right to modify the below contents at any moment without prior notice.

MODEL	SP5	SP8	SP7	SP10	SP13
<i>Use</i>	Indoor	Indoor	Outdoor	Outdoor	Outdoor
<i>LEDs per Pixel</i>	2R, 1G, 1B (SMD)	2R, 1G, 1B (SMD)	2R, 1G, 1B (TH)	2R, 1G, 1B (TH)	2R, 1G, 1B (TH)
<i>Visible Pitch – mm</i>	5,08	8	7,8125	10	13,75
<i>Panel Size – mm</i>	650x487x165	1024x768x165	1000x750x335	1280x960x335	1320x880x335
<i>Visible Panel Graphic Definition</i>	128x96	128x96	128x96	128x96	96x64
<i>Horizontal Viewing Angle</i>	160°	160°	160°	160°	160°
<i>Vertical Viewing Angle</i>	160°	160°	60°	60°	60°
<i>Visible Resolution – Px/sqm</i>	38.750	15.625	16.384	10.000	5.289
<i>Brightness – NIT</i>	~1.800	~2.000	~7.300	~6.400	~6.500
<i>Refresh Rate – Hz</i>	1.000	1.000	1.000	1.000	1.000
<i>Medium Consumption – Kw/Panel</i>	0,18	0,4	0,38	0,56	0,20
<i>Weight – Kg./Panel</i>	22	35	68	75	65

Note: with the horizontal and vertical numbers of the screen type panels, you can create the screen sizes, which meet your request.

ELETRONIC CONTROL SYSTEM FOR EVENT

DLX Live-SD DLX Live-X HD DLX Live-SX HD DLX Live-WUX

ACCESSORIES	
Spare Parts KIT	Power Box & Cable
DLX Pro-II	Flight Case
Fiber Optic	Trailer 12m ² Display
RJ2bnc-2 Converter	Spider System 12m ² Display
RJ2bnc-2 Converter (80m)	Container 29m ² Display
RJ2bnc-2 Converter (200m)	Container 42m ² Display
DLX Box Opto-X	Container 84m ² Display
DLX Box Opto-SX	Windload Support up to 20m ²
DLX Box Opto-WUX	Windload Support over 20m ²